

RECESED DOWNLIGHT

MATRIX RANGE

INDOOR

RECESED DOWNLIGHT



bridgelux®

CREE

OSRAM

SAMSUNG



PRODUCT OVERVIEW

ITEM Code	680101439932	680101439949
DWG.Code	F5	F10
Family Name	MATRIX RANGE	MATRIX RANGE
Power	7W	14W
Input Voltage	85-240V	85-240V
LED CHIP BRAND	Bridgelux/samsung/Cree/Osram	Bridgelux/samsung/Cree/Osram
CRI	Ra≥90 / Ra≥95 (On request)	Ra≥90 / Ra≥95 (On request)
CCT	2700K/3000K/4000K/6500K	2700K/3000K/4000K/6500K
Beam Angle	24*/36*/60*	24*/36*/60*
Lamp Cup	Black / White	Black / White
IP Rating	IP20 / IP 40	IP20 / IP 40
Driver Type	LIFUD/EAGLERISE/SWARVEN	LIFUD/EAGLERISE/SWARVEN
Material	Aluminum / Heat Sink	Aluminum / Heat Sink
Cutout	156*35	306*35
Dimention	L 162*40*43	L 312*40*43
Manufacturer's Warranty	5 years	5 years
Installation method	Recessed Downlight	Recessed Downlight

Swarven web : <https://swarven.com/>

Lumen efficiency can be increased upon request and based on the required quantity.

For coding pearpose ,

1-CCT :- For 2700K add W to code, For 3000k add L to code, For 4000K add D to code, for 6500K add S to code & For Tunable(2700K-6500K) add Z to code

2- Voltage : Put the number of the voltage (7 or 12)

3- Beam angle : Put the number of the Angle (24* or 38*)

4- Put I with No. that need IP (20*40*&44*) (Ex : CR- Code , 7- W , 2700K - K , 24*- Beam Angle , IP20 - IP rating , D - Dali)

5- Driver : (Triac, Leading Edg, 0-10v,1-10v,zigbee & dally on required) (On / Off)ST , Trick (T) , (0 - 10 v) V , (1 - 10 v) V1 & Dali (D)

Emergancy add EM to code (EM - Emergancy)