

## MOON RANGE - WALL LIGHT

### WALL REFLECT

## OUTDOOR

### MOON RANGE - REFLECT



bridgelux®

CREE

OSRAM

SAMSUNG



#### PRODUCT OVERVIEW

|                         |                                            |
|-------------------------|--------------------------------------------|
| Item Code               | 699246210030                               |
| Code                    | WL4                                        |
| Product Name            | Moon Range                                 |
| Power                   | 14W                                        |
| Input Voltage           | AC200-240V                                 |
| Total Lumen Efficiency  | 925 lum                                    |
| LED CHIP BRAND          | Bridgelux/samsung/Cree/Osram               |
| CRI                     | Ra≥90 / Ra≥95 (On request)                 |
| CCT                     | 3000K / 4000K/6000K                        |
| Beam Angle              | 100°                                       |
| Lamp Cup                | Dark Grey , Corten                         |
| IP Rating               | IP65                                       |
| Driver Type             | EAGLERISE/MW/SWARVEN                       |
| Material                | Aluminum                                   |
| Dimention               | Φ220*112*93                                |
| Manufacturer's Warranty | 5 years                                    |
| Installation method     | Black cover + Black housing - Wall mounted |

Swarven web : <https://swarven.com/>

Lumen efficiency can be increased upon request and based on the required quantity.

For coding pearpose ,

1-CCT :- For 2700K add W to code, For 3000k add L to code, For 4000K add D to code, for 6500K add S to code & For Tunable(2700K-6500K) add Z to code

2- Voltage : Put the number of the voltage ( 7 or 12 )

3- Beam angle : Put the number of the Angle (24\* or 38\* )

4- Put I with No. that need IP ( 20\*40\*&44\* ) ( Ex : CR- Code , 7- W ,2700K - K, 24\*- Beam Angle , IP20 - IP rating , D - Dali )

5- Driver : ( Triac, Leading Edg, 0-10v,1-10v,zigbee & dally on required) ( On / Off )ST , Trick ( T ) , ( 0 - 10 v ) V , ( 1 - 10 v ) V1 & Dali ( D )

6- Emargency add EM to code ( EM - Emargency)